


Complaint



IIC: 04015001-P0015774

www.act-connectivity.com



DETAIL A

Partnumber	Length	Tolerance
RL9500	0.5M	0/+100mm
RL9501	1M	0/+100mm
RL9551	1.5M	0/+100mm
RL9502	2M	0/+100mm
RL9503	ЗМ	0/+100mm
RL9505	5M	0/+100mm

Partnumber	Length	Tolerance
RL9510	10M	0/+100mm
RL9515	15M	0/+100mm
RL9520	20M	0/+100mm
RL9525	25M	0/+100mm
RL9530	30M	0/+150mm
RL9550	50M	0/+250mm

ITEM	Description	Q'TY
1	LC dust cover white	4 PCS
2	LC/UPC MM duplex connector beige	2 PCS
3	LC clip beige	2 PCS
4	LC short boot white L=19.5±0.5mm	2 PCS
5	LC short boot vellow L=19.5±0.5mm	2 PCS

LC/UPC --- LC/UPC duplex (1.9±0.1)*(4.0±0.2)mm OM2 LSZH Orange

I	LC dust cover white	4 503
2	LC/UPC MM duplex connector beige	2 PCS
3	LC clip beige	2 PCS
4	LC short boot white L=19.5±0.5mm	2 PCS
5	LC short boot yellow L=19.5±0.5mm	2 PCS
6	LC heat-shrink tube white	2 PCS
7	LC heat-shrink tube yellow	2 PCS
8	Breakout heat-shrink tube black L=15mm	2 PCS
9	Cable lable	1 PC
10	OD=(1.9±0.1)*(4.0±0.2)mm duplex OM2 fiber optical cable LSZH Orange	1 PC

ACT			
Designed by:		Audit:	
Date:	2021-06-23	Approve:	
Unit:	mm	Sheet:	A4
Drawing NO:	RL95xx LC/UPC-LC/UPC duplex patchcord OM2-V1		





Product Specification

Standard Compliances

- 1. ANSI/TIA-568.3-D.
- 2. ISO 11801 OM1 /IEC60793-2-10 type A1a.
- 3. Telcordia GR-326-CORE Issue 4 February 2010 Compliance.
- 4. RoHS Compliance for the Requirement of European Union Issued Directive 2011/6S/EU.

Construction&Characteristics

	Insertion loss typical	0.15dB	
Ontical Parformance	Insertion loss maximum	0.25dB	
Optical Performance	Return loss	≥30dB	
	Polish	UPC	
	Connector A side	IEC61754-20 LC connector	
Connector	Connecter B side	IEC61754-20 LC connector	
	Ferrule	Ceramic Zirconia (Zr02)	
	Fiber class	OM2	
	Fiber type	Multimode 50/125	
Cabla	Cable type	(1.9±0.1)*(4.0±0.2)mm LSZH Orange	
Cable	Tensile strength	200N (short time 400N)	
	Operation temp.	-20 °Cto +80 °C (5 cycles)	
	Vibration	10 to 55 Hz 15mm double amplitude	
Marking	ACT Premium Multimode Fiber Optic Patch cable 50/125µm,OM2,LSZH xxxxM		

100% tested and approved

- 1. ACT advices to clean every connector ferrule before usage to get optimal performance.
- 2. Always leave the dust caps on if the cable isn't installed.